


ART. PC-C Diritto filetto cilindrico maschio
Straight male parallel adaptor

CODICE	ØD	ØF	L1	L2	⊙	🔧	📦
PC03-M3C	3	M3x0,5	3,5	15		8	10
PC03-M5C	3	M5x0,8	3,5	16	2	8	10
PC03-M6C	3	M6x1,0	4	16	2	8	10
PC03-01C	3	R 1/8	7,5	15	2	10	10
PC03-G01C	3	G 1/8	5,5	14,6	2	14	10
PC04-M3C	4	M3x0,5	3,5	17,5		8	10
PC04-M5C	4	M5x0,8	3,5	18,5	2	8	10
PC04-M6C	4	M6x1,0	4	19	2	10	10
PC04-01C	4	R 1/8	7,5	16	3	10	10
PC04-G01C	4	G 1/8	5,5	15,2	3	14	10
PC04-G02C	4	G 1/4	7,5	17,2	3	17	10
PC06-M3C	6	M3x0,5	3,5	18		10	10
PC06-M5C	6	M5x0,8	3,5	18	2	10	10
PC06-M6C	6	M6x1,0	4	18,5	2	10	10
PC06-01C	6	R 1/8	7,5	18,5	4	10	10
PC06-G01C	6	G 1/8	5	17,2	4	13	10
PC06-G02C	6	G 1/4	7,5	18,5	4	17	10


ART. POC-C Diritto corpo cilindrico filetto maschio
Straight male cylindrical body adaptor

CODICE	ØD	ØF	L1	L2	ØD1	ØD2	⊙	🔧
POC03-M3C	3	M3x0,5	3,5	15	6,5	7,5		10
POC03-M5C	3	M5x0,8	3,5	16	8	7,5	2	10
POC03-M6C	3	M6x1,0	4	16	8	7,5	2	10
POC03-G01C	3	G 1/8	5,5	14,6	14	7,5	2	10
POC04-M3C	3	M3x0,5	3,5	17,5	8	10		10
POC04-M5C	4	M5x0,8	3,5	18	8	10	2	10
POC04-M6C	4	M6x1,0	4	18,5	8	10	2	10
POC04-01C	4	R 1/8	7,5	15,5	10	10	3	10
POC04-G01C	4	G 1/8	5,5	15,2	14	10	3	10
POC04-G02C	4	G 1/4	7,5	17,2	17	10	3	10
POC06-M3C	6	M3x0,5	3,5	18	10	11,5		10
POC06-M5C	6	M5x0,8	3,5	18	10	11,5	2	10
POC06-M6C	6	M6x1,0	4	18,5	10	11,5	2	10
POC06-01C	6	R 1/8	7,5	18,5	10	11,5	4	10
POC06-G01C	6	G 1/8	5,5	17,6	14	11,5	4	10
POC06-G02C	6	G 1/4	7,5	18,5	17	11,5	4	10

